

VERDIN ALPHA II Controller

- Daylight Savings Time Change Instructions -



444 Reading Road
Cincinnati, Ohio 45202
800-543-0488
513-241-1855 fax

Copyright ©The VERDIN Company 2007

VERDIN ALPHA II Controller
- Daylight Savings Time Change Instructions -
DAYLIGHT SAVINGS DISABLE



Disable Step 1
Press
MENU/CANCEL

VERDIN ALPHA II Controller

- Daylight Savings Time Change Instructions -

DAYLIGHT SAVINGS DISABLE



Disable Step 2
Press SETUP

VERDIN ALPHA II Controller
- Daylight Savings Time Change Instructions -
DAYLIGHT SAVINGS DISABLE



Disable Step 3
Press DST

VERDIN ALPHA II Controller
- Daylight Savings Time Change Instructions -
DAYLIGHT SAVINGS DISABLE



Disable Step 4
Press
DISABLE

VERDIN ALPHA II Controller
- Daylight Savings Time Change Instructions -
DAYLIGHT SAVINGS DISABLE



Disable Step 5
Press
MENU/CANCEL

VERDIN ALPHA II Controller
- Daylight Savings Time Change Instructions -
DAYLIGHT SAVINGS DISABLE



Disable Step 6
Press
MENU/CANCEL

VERDIN ALPHA II Controller
- Daylight Savings Time Change Instructions -
DAYLIGHT SAVINGS DISABLE



Disable Step 7
Press
MENU/CANCEL

VERDIN ALPHA II Controller
- Daylight Savings Time Change Instructions -
DAYLIGHT SAVINGS DISABLE



Disable Step 8
Press
MENU/CANCEL

VERDIN ALPHA II Controller

- Daylight Savings Time Change Instructions -



Step 1
Press
'Menu/Cancel'

VERDIN ALPHA II Controller

- Daylight Savings Time Change Instructions -



Step 2
Press
'Clock'

VERDIN ALPHA II Controller

- Daylight Savings Time Change Instructions -



Step 3
Press the current day
of the week. In this
example it is
'Mon'

VERDIN ALPHA II Controller

- Daylight Savings Time Change Instructions -



Step 4
Using the two digit method, enter the current month. In this example it is March, so you would Press '0 Then 3'

VERDIN ALPHA II Controller

- Daylight Savings Time Change Instructions -



Step 5
Using the two digit method, enter the current date. In this example it is 12th, so you would Press '1 Then 2'

VERDIN ALPHA II Controller

- Daylight Savings Time Change Instructions -



Step 6

Using the two digit method, enter the current year. In this example it is 2007, so you would Press '0 Then 7'

VERDIN ALPHA II Controller

- Daylight Savings Time Change Instructions -



Step 7

Using the four digit method, (HH MM) enter the current time. In this example it is 9:03am, so you would Press '0, 9, 0, 3'

VERDIN ALPHA II Controller

- Daylight Savings Time Change Instructions -



Step 8
Press
'Enter'

VERDIN ALPHA II Controller

- Daylight Savings Time Change Instructions -



Step 9
Press
'Menu/Cancel'

VERDIN ALPHA II Controller

- Daylight Savings Time Change Instructions -



Finished